

Model TBR-160-S Neutralizing Kit

In some installations, addition of the TBR-160-S to Model HF6V detunes 10 meters. This kit restores 10 meter tuning,

1. Attach clamp with capacitor to antenna as shown in diagram. Placement is not critical.
2. Attach lead from capacitor to the 2nd or 3rd turn up from the bottom of the 160 meter coil.
3. Tap upward on the 160 meter coil until the 10 meter resonance curve moves into the band.
4. Complete tuning by readjusting the 160 meter coil as needed to compensate for the loading effect of the neutralizing capacitor. You will have to stretch the 160 meter coil a bit.